

Quick Start Guide

Livio Edge Al | Livio Al | Livio



At Starkey, we believe that to hear better is to live better.

Livio Edge AI, Livio AI and Livio Rechargeable hearing aids help you stay connected to the people and things you love most. These 2.4 GHz hearing aids offer Starkey's most advanced technology with supreme sound quality and features, customizable to fit your unique hearing needs.

Get the most out of your hearing aids

Please visit **starkey.com.au/support** for additional tools and resources including:

- Instructional videos
- Operations manuals
- Product brochures



Charging Your Hearing Aids



- Place your hearing aids in the charger with the earbuds or earmolds resting inside the reservoir.
- Your hearing aids will turn off automatically and begin to charge. Standard charger requires external power source (i.e. wall outlet).
- Note: The LEDs corresponding to each hearing aid:
 - Glowing Green = Charging
 - Solid Green = Fully Charged
 - Blinking Red = Fault State. To reset, remove the hearing aids from charger, wait until LED turns off and re-insert aids. If Fault State continues, call your hearing professional.

- Charging occurs with the lid open or closed; hearing aids will be fully charged in under 3 1/2 hours.
- It is safe to store hearing aids in the charger after they are fully charged and any time that you are not wearing them.
- Hearing aids will automatically power on when removed from the charger. Standard charger requires external power source (i.e. wall outlet).
- The desiccant puck provided will be effective for 3–6
 months depending on moisture in the hearing aids and
 humidity. When the desiccant puck fades from blue to
 white, it should be replaced.
- If you will not be wearing your hearing aids for an extended period of time (i.e, weeks), remove both the plug from the charger and the hearing aids from the charging ports. You will need to manually power off the hearing aids by pressing the user control on each hearing aid for three seconds.

Ask your hearing professional about our pocket-sized Mini Turbo Charger that provides a 3.5-hour charge in just seven minutes.



4 5

Power On & Off

- **ON** The hearing aids will power on automatically after removing them from the charger. There is a delay that allows you time to insert your hearing aid into your ear.
- **ON** If the hearing aid is manually powered off, pressing the user control for three seconds will power it on. The delay still exists, to give you time to insert the hearing aid into your ear.
- **OFF** The hearing aids will power off automatically when placed in the charging port. Charging will proceed.
- **OFF** The hearing aids can be powered off manually by pressing the user control for three seconds.

System Care

HEARING AID CARE

Keep your hearing aid clean. Heat, moisture and foreign substances can result in poor performance.

- Use a cleaning brush or soft cloth to clean debris from around the user control, microphone and battery compartment.
- Inspect the receiver, earbud and wax guard regularly.

 Never use water, solvents, cleaning fluids or oil to clean your hearing aid.

CHARGER CARE

Keep your charger clean. Heat, moisture and foreign materials can result in poor performance.

- Use the provided cleaning brush to keep the charging ports and hearing aid microphones clear of debris.
- Do not use water, solvents or cleaning fluids to clean the charging ports.
- Keep lid closed as much as possible to avoid dust and debris buildup.
- Store your charger in a clean and dry location i.e., a dresser or shelf rather than the bathroom or kitchen.

To ensure the longest life of your rechargeable hearing aid batteries:

- Fully charge hearing aid batteries every night.
- Do not expose to excess heat, i.e., do not store on a window sill or in a hot car.

6

Helpful Hints


- Do not take apart your hearing aids or insert the cleaning tools inside them.
- When not in use, place your hearing aid in the storage container and store:
 - In a dry, safe place
 - Away from direct sunlight and heat to avoid extreme temperatures
 - Where you can easily find them
 - Safely out of reach from children and pets

Hear Clear Receiver Wax Guards

RIC hearing aids integrate disposable Hear Clear earwax protection. The innovative wax guards prevent earwax accumulation in the hearing aid receiver. When you need to replace your wax guards, please follow the instructions below.

- 1. Insert empty end of the application stick straight into used wax guard in hearing aid.
- 2. Pull **straight** out (do not twist) on stick to remove used wax guard.

- 3. Use opposite end of stick to firmly insert clean wax guard straight into hearing aid.
- 4. Pull **straight** out (do not twist) to remove stick and discard.



Download and Connect to the Thrive (thrive) **Hearing Control App**



The Thrive Hearing Control app makes it easy to control and adjust your 2.4 GHz rechargeable hearing aids with your compatible Apple® or Android™ device. Downloading and connecting to the app is easy; refer to the Thrive Hearing Control app User Guide or visit starkey.com/thrivesupport for additional information, such as:

- Integrated sensors and artificial intelligence features*
- Automatic and custom memories
- Geotags
- SoundSpace
- Tinnitus management
- Find My Hearing Aids
- Alerts

Visit starkey.com/thrivesupport for compatibility information. *Available with Livio Edge AI and Livio AI hearing aids only.

Hearing Aid Information

| Hea | ring aid mode | : | | |
|-------------------------------|------------------|-------------------------------------|----------------|--|
| Hearing aid serial number: LR | | | | |
| Cha | rger serial num | nber: | | |
| War | ranty expiratio | n date: | | |
| Men | nory settings, i | f applicable: | | |
| | Memory # | Environment/ Listening Situation | Beep/Indicator | |
| | | | | |
| | | | | |
| | | | | |
| | | | | |
| ••••• | | | | |
| Spe | cial instruction | s: | | |
| | | | | |
| | | | | |
| | | | | |
| Не | aring professio | onal: | | |
| | | | | |
| | | | | |
| | | | | |

M/T Ratings

| | М | Т |
|------------------|---|---|
| RIC Rechargeable | 4 | 4 |
| BTE Rechargeable | 4 | 4 |

For Thrive Hearing Control app and iOS/Android compatibility information, please visit starkey.com/thrivesupport.

Apple, the Apple logo, iPhone, iPad and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries. App Store is a registered service mark of Apple Inc.

Android and Google Play are trademarks of Google LLC.

The Starkey Logo, Livio, Livio logo, Starkey, Thrive and SoundSpace are registered trademarks of Starkey Laboratories, Inc.

The Thrive logo is a trademark of Starkey Laboratories, Inc.



Starkey.com

6700 Washington Ave. S. Eden Prairie, MN 55344 1.800.328.8602





