HDMI® MATRIX SWITCH







CS-44MHD2
HDMI® MATRIX SWITCH





PRODUCT OVERVIEW

The 18Gbps 4x4 HDBaseT (150M) Matrix can connect 4 HDMI® sources to 8 displays. It features 4 HDMI® outputs and each HDMI® output is mirrored to provide a CAT-Cable output which runs simultaneously. Audio de-embedded to analog and coaxial audio is supported. Each HDMI® output supports 4K to 1080P downscaling independently. The IR signal is one-to-one control at the Matrix end, but the IR signal follows HDMI® video channel at the HDBaseT Receiver end.



- Video resolution up to 4K/60Hz (YUV 4:4:4) on all HDMI® & HDBaseT ports
- 4 HDMI® inputs, 4 HDMI® & HDBaseT mirrored outputs
- HDMI® ports transmit 18Gbps lossless uncompressed video bandwidth
- Supports 18Gbps lossless compressed HDBaseT signal transmission & 4K->1080P Down Scaler for each output port
- HDR, HDR10, HDR10+, Dolby Vision™, HLG, and IR matrix are supported
- HDBaseT output can extend video transmission distance up to 492ft/150m for 1080P or 394ft/120m for 4K/60 via a single Cat 5e/6/7 cable with 24V POC on all HDBaseT ports
- HDMI® audio pass-through up to 7.1CH HD audio (LPCM, Dolby™ TrueHD and DTS-HD Master Audio)
- Audio de-embedded is supported via analog and coax ports
- Advanced EDID management and CEC control are supported
- 1U rack mounted design with front panel OLED display
- Control via front panel buttons, IR remote, RS-232, LAN and Web GUI



www.EtherealPro.com | 386-255-0234 © COPYRIGHT 2024 Ethereal 7/24

AWARNING INGESTION HAZARD ● DEATH or serious injury can occur ● A swallowed button cell or coin batte ry can cause Internal Chemical Burns in as little as 2 hours ● KEEP new and used batteries OUT OF REACH OF CHILDREN ● Seek immediate medical attentio n if a battery is suspected to be swallowed or inserted inside any part of the body ● For treatment information call the National Batte ry Ingestion Hotline at: 1-800-498-8666

